

PRODUCT-DETAILS

E 93HN/20

E 93HN/20 Fuse holder



General Information

Extended Product Type	E 93HN/20
Product ID	2CSM200933R1801
EAN	8012542009337
Catalog Description	E 93HN/20 Fuse holder
Long Description	E 93HN/20 is a fuseholder for overcurrent and short circuit protection. No blown fuse indicator.

Ordering

EAN	8012542009337
Minimum Order Quantity	1 piece
Customs Tariff Number	85361010

Dimensions

Product Net Width	0.053 m
Product Net Height	0.085 m
Product Net Depth / Length	0.064 m
Product Net Weight	0.192 kg

Container Information

Package Level 1 Units	2 piece
Package Level 1 Width	0.105 m
Package Level 1 Height	0.085 m
Package Level 1 Depth / Length	0.064 m
Package Level 1 Gross Weight	0.387 kg
Package Level 1 EAN	8012542009344

Environmental

RoHS Status	Following EU Directive 2011/65/EU
-------------	-----------------------------------

Additional Information

Degree of Protection	IP20
Dimensions	1 module
Fuse Size	8.5x31.5 mm
Mounting Type	DIN rail
Number of Poles	4
Number of Protected Poles	3
Options Provided	No
Position of Neutral Terminals	Right
Power Loss	at Rated Operating Conditions per Pole 3 W
Product Main Type	E 90
Product Name	Fuse holder
Rated Current (I_n)	20 A
Rated Frequency (f)	50...60 Hz
Rated Voltage (U_r)	690 V
Rated Operational Voltage	690 V AC
RoHS Date	1/1/2014
Voltage Range	690 V AC

Certificates and Declarations (Document Number)

Data Sheet, Technical Information	2CSC444002B0204
Declaration of Conformity - CE	2CSC444001D2701
Environmental Information	See RoHS Information
Instructions and Manuals	on the product body
RoHS Information	2CSC444011K2701

Classifications

ETIM 4	EC000036 - Miniature fuse holder
ETIM 5	EC000036 - Miniature fuse holder
ETIM 6	EC002705 - Holder for cylindrical fuse
ETIM 7	EC002705 - Holder for cylindrical fuse
Object Classification Code	F
WEEE Category	5. Small Equipment (No External Dimension More Than 50 cm)

Categories

Low Voltage Products and Systems → Modular DIN Rail Products → Protection and Safety devices → Cylindrical Fuse Holders and Fuse Switch Disconnectors

